



Part No. SRFS 70WCANKPC

WR137 WAVEGUIDE TO COAXIAL ADAPTER RIGHT

Mechanical Specification	
Waveguide Type	WR137
Material	Copper
Connector Type	N Female
Flange Type	FDP70(Cover)
Inside Finish	Silver Plating
Outside Finish	Anticorrosion Grey Paint

Electrical Specification	
Frequency Range	5.38 -8.17 GHz
VSWR (Max)	1.25

Signity RF Solutions offers a standard product line of waveguide to Coaxial Adapter (Right angle) Covering a full frequency range for rectangular waveguides, with multiple flange and coaxial type and specification configuration available