



Part No. SRFS 6WCANKPA

WR1500 WAVEGUIDE TO COAXIAL ADAPTER RIGHT ANGLE

Mechanical Specification	
Waveguide Type	WR1500
Material	Aluminium
Connector Type	N Female
Flange Type	FDP6(Cover)
Inside Finish	Chromate Conversion
Outside Finish	Corrosion protected with grey paint

Electrical Specification	
Frequency Range	0.49 – 0.75 GHz
VSWR (Max)	1.30

Signity RF Solutions offers a standard product line of waveguide to Coaxial Adapter (Right angle) Covering a full frequency range for rectangular waveguides, with multiple flange and coaxial type and specification configuration available