



Part No. SRFS 260WECASKPC

WR34 WAVEGUIDE TO COAXIAL ADAPTER END LAUNCH

Mechanical Specification

Waveguide Type	WR34
Material	Copper
Connector Type	SMA Female
Flange Type	FBP260(Cover)
Inside Finish	Silver Plating
Outside Finish	Anticorrosion Grey Paint

Electrical Specification

Frequency Range	21.7– 33 GHz
VSWR (Max)	1.50

Signity RF Solutions offers a standard product line of waveguide to Coaxial Adapter (Right angle) Covering a full frequency range for rectangular waveguides, with multiple flange and coaxial type and specification configuration available