



Part No. SRFS 40WCANKPA

## WR340 WAVEGUIDE TO COAXIAL ADAPTER RIGHT ANGLE

Mechanical Specification	
Waveguide Type	WR340
Material	Aluminium
Connector Type	N Female
Flange Type	FDP26(Cover)
Inside Finish	Passivation
Outside Finish	Anticorrosion Grey Paint

Electrical Specification	
Frequency Range	2.17 3.39 GHz
VSWR (Max)	1.25

Signity RF Solutions offers a standard product line of waveguide to Coaxial Adapter (Right angle) Covering a full frequency range for rectangular waveguides, with multiple flange and coaxial type and specification configuration available