



WR112 WAVEGUIDE H-BEND

Mechanical Specification	
Waveguide Type	WR112
Material	Copper
Inside Finish	Silver Plating
Outside Finish	Anticorrosion Grey Paint
Flange Type	FBP84 (UG-51/U, SQ Cover)
Dimensions	A=60 mm, B=60 mm

Electrical Specification	
Frequency Range	8.5-9.6 GHz
VSWR (Max)	1.10
Insertion Loss	0.2 dB

Signity RF Solutions offers a standard product line of *E Bend* and *H Bend* covering waveguide sizes WR10 thru WR430. Additional size and Configuration can be custom made as per customer's specific requirements.

