



WR12 WAVEGUIDE E-BEND

| Mechanical Specification | |
|--------------------------|-------------------|
| Waveguide Type | WR12 |
| Material | Copper |
| Finish | Gold Plating |
| Length | A=20 mm, B=20mm |
| Flange Type | FUGP740 (UG387/U) |

| Electrical Specification | |
|--------------------------|---------------|
| Frequency Range | 60.5-91.9 GHz |
| VSWR (Max) | 1.15 |

Signity RF Solutions offers a standard product line of *E Bend* and *H Bend* covering waveguide sizes WR10 thru WR430. Additional size and Configuration can be custom made as per customer's specific requirements.

