



## Signity RF Solutions







Part No. SRFS 48WCASKPA

## WR187 WAVEGUIDE TO COAXIAL ADAPTER END LAUNCH

Mechanical Specification	
Waveguide Type	WR187
Material	Aluminum
Connector Type	SMA Female
Flange Type	FDP48(Cover)
Inside Finish	Chromate Conversion
Outside Finish	Anticorrosion Grey Paint

Electrical Specifiation		
Frequency Range	3.94– 5.99 GHz	
VSWR (Max)	1.25	

Signity RF Solutions offers a standard product line of waveguide to Coaxial Adapter Covering a full frequency range for rectangular waveguides, with multiple flange and coaxial type and specification configuration available