



Part No. SRFS 40WCANKPA

WR229 WAVEGUIDE TO COAXIAL ADAPTER RIGHT ANGLE

| Mechanical Specification | |
|--------------------------|--------------------------|
| Waveguide Type | WR229 |
| Material | Aluminium |
| Connector Type | N Female |
| Flange Type | FDP40(Cover) |
| Inside Finish | Passivation |
| Outside Finish | Anticorrosion Grey Paint |

| Electrical Specification | |
|--------------------------|---------------|
| Frequency Range | 3.22 -4.9 GHz |
| VSWR (Max) | 1.25 |

Signity RF Solutions offers a standard product line of waveguide to Coaxial Adapter (Right angle) Covering a full frequency range for rectangular waveguides, with multiple flange and coaxial type and specification configuration available