



Part No. SRFS 320WECASKPC

## WR28 WAVEGUIDE TO COAXIAL ADAPTER END LAUNCH

Mechanical Specification	
Waveguide Type	WR28
Material	Copper
Connector Type	SMA Female
Flange Type	FBP320(Cover)
Finish	Gold Plating

Electrical Specification	
Frequency Range	26.5– 40 GHz
VSWR (Max)	1.35

Signity RF Solutions offers a standard product line of waveguide to Coaxial Adapter (Right angle) Covering a full frequency range for rectangular waveguides, with multiple flange and coaxial type and specification configuration available