



Part No. SRFS 320WCA2.92KPC

## WR28 WAVEGUIDE TO COAXIAL ADAPTER RIGHT ANGLE

Mechanical Specification	
Waveguide Type	WR28
Material	Copper
Finish	Gold Plating
Connector	2.92 mm Female
Flange Type	FBP320 (Cover)

Electrical Specification	
Frequency Range	26.5 – 40 GHz
VSWR (Max)	1.25
Insertion Loss	0.3 dB

Signity RF Solutions offers a standard product line of waveguide to Coaxial Adapter (Right angle) Covering a full frequency range for rectangular waveguides, with multiple flange and coaxial type and specification configuration available