



Part No. SRFS 32WECANKPA

WR340 WAVEGUIDE TO COAXIAL ADAPTER END LAUNCH

Mechanical Specification	
Waveguide Type	WR340
Material	Aluminum
Connector Type	N Female
Flange Type	FDP26(Cover)
Inside Finish	Chromate Conversion
Outside Finish	Anticorrosion grey Paint

Electrical Specification	
Frequency Range	2.17– 3.3GHz
VSWR (Max)	1.25

Signity RF Solutions offers a standard product line of waveguide to Coaxial Adapter Covering a full frequency range for rectangular waveguides, with multiple flange and coaxial type and specification configuration available