



Part No. SRFS 220WECASKPC

## WR42 WAVEGUIDE TO COAXIAL ADAPTER END LAUNCH

Mechanical Specification	
Waveguide Type	WR42
Material	Copper
Connector Type	SMA Female
Flange Type	FBP220(Cover)
Inside Finish	Silver Plating
Outside Finish	Anticorrosion Black Paint

Electrical Specification	
Frequency Range	18.0– 26.5 GHz
VSWR (Max)	1.40

Signity RF Solutions offers a standard product line of waveguide to Coaxial Adapter (Right angle) Covering a full frequency range for rectangular waveguides, with multiple flange and coaxial type and specification configuration available