



Part No. SRFS 220WCASKPC

WR42 WAVEGUIDE TO COAXIAL ADAPTER RIGHT ANGLE

Mechanical Specification	
Waveguide Type	WR42
Material	Copper
Finish	Gold Plating
Connector	SMA Female
Flange Type	FBP220(Cover)
Inside and Outside Finish	Silver Plating
Outside Finish	Anticorrosion grey paint

Electrical Specification	
Frequency Range	17.6 – 26.7 GHz
VSWR (Max)	1.35

Signity RF Solutions offers a standard product line of waveguide to Coaxial Adapter (Right angle) Covering a full frequency range for rectangular waveguides, with multiple flange and coaxial type and specification configuration available